



Litepanels® 2x2 Portable Frame Assembly Instructions



1. Remove the yoke from each of the four Litepanels® 1x1 fixtures.
2. Place the four Litepanels® 1x1 fixtures face down and apply the horizontal cross member with the bent sides down.
3. Apply the vertical cross member over this and adjust each Litepanels® 1x1 fixture to line-up the screw holes.
4. Use the twelve fastening knobs to secure the cross members to the four Litepanels® 1x1 fixtures.
5. Attach Yoke-sides to Yoke-bottom with the bent section to the inside and fasten with screws and washers.
6. Fit threaded T-handles through holes in the Yoke-sides.
7. Apply flat side of rubber washers over threaded T-handles.
8. Attach the completed Yoke assembly to the Litepanels® 2x2 frame assembly, thread T-handles and tighten.
9. Mount the entire Litepanels® 2x2 frame/fixture assembly onto a tripod stand and secure with T-handle.
10. An optional, dedicated Litepanels® 2x2 power supply may be attached to the horizontal cross member of the Litepanels® 2x2 frame for dimmer/power control.

Litepanels, Inc.

www.litepanels.com

15162 Saticoy Street, Van Nuys, CA 91406

Tel: 818-752-7009 – Fax: 818-752-2437 – Info@litepanels.com



Litepanels® 2x2 Frame-Solid Yoke **Assembly Instructions**

1. Remove the yoke from each of the four Litepanels® 1x1 fixtures.
2. Place the four Litepanels® 1x1 fixtures face down and apply the horizontal cross member with the bent sides down.
3. Apply the vertical cross member over this and adjust each Litepanels® 1x1 fixture to line-up the screw holes.
4. Use the twelve fastening knobs to secure the cross members to the four Litepanels® 1x1 fixtures.
5. Attach 3/8” Hex Bolt with steel washer through left side of Yoke, then apply a second steel washer over threads and screw into frame assembly by tightening with the enclosed “nut” to the end of the screw.
6. Using the 3/8” T-handle and steel washers, repeat process to attach yoke to right side of frame. (Steel washers are slightly cupped and applied in toward frame)
7. Mount the entire Litepanels® 2x2 frame/fixture assembly onto a tripod stand and secure with stand hardware/Junior Stud.
8. Attach the dedicated Litepanels® 2x2 power supply to the horizontal cross member of the Litepanels® 2x2 frame with supplied hardware.
9. Attach four connector/cable assemblies between the power supply and each of the Litepanels® 1x1 fixtures.
10. Apply power and the Litepanels® 2x2 is ready for operation.

Litepanels, Inc.

www.litepanels.com

15162 Saticoy Street, Van Nuys, CA 91406

Tel: 818-752-7009 – Fax: 818-752-2437 – Info@litepanels.com